CMS system. User Guide to installation.

CMS is software that does allow you to view your CCTV using laptop or computer. Herewith is the guide to install the system.

- 1. Download the software by the given link.
- 2. Install (Run) the software.



3. Follow this step by step instructions.



刘 🗢 📕 « English 🕨 Software 🕨	v 4 ₇	Search Software	_
Organize 👻 Burn to disc		80 - 🗂	
A Name	Date modified	Туре	
Files Currently on the Disc (18)			
💄 🔋 🔑 AVI plugin	2/12/2013 4:12 PM	File folder	
CMS	2/12/2013 4:12 PM	File folder	
Diskplayer	2/12/2013 4:12 PM	File folder	
H.264 Video player	2/12/2013 4:12 PM	File folder	
H264Play	2/12/2013 4:12 PM	File folder	
🧧 📰 🛛 👪 Hard disk player	2/12/2013 4:12 PM	File folder	
🚆 🛛 👪 IE plugin	2/12/2013 4:12 PM	File folder	
E IEActive	2/12/2013 4:12 PM	File folder	
🔹 📕 Language	2/12/2013 4:12 PM	File folder	
MediaPlay plugin	2/12/2013 4:12 PM	File folder	
Mobile Monitor	2/12/2013 4:12 PM	File folder	
NetSDK	2/12/2013 4:12 PM	File folder	
Player	2/12/2013 4:12 PM	File folder	
C Upgrade	2/12/2013 4:12 PM	File folder	
🚽 🛯 📕 Upgrade tool	2/12/2013 4:12 PM	File folder	



4. Click (Next) to continue as the picture shown below.



5. The shortcut will appear at the desktop.



2222222	
Português(BR)	
English	
Französisch	
DEUTSCHER	
e/////	
Hebrew	
hunganan	

6. The login "username" and "password" will be the password as set at the DVR.



7. Entering the CMS system.



8. Click system to add the DVR.

9. Click the Device Manager

– = ×

Time 12:09:20 2016-09-10

System

Local Config



10. Create new zone list to add the device.



11. Add the device as shown below.

e Manager			_			
	Zone List	ADD DEV	лсе_	Î		

12. Click the IP Search to find your DVR IP

13. Click at the Ip Adress that shown. This Ip address is the DVR Ip address in which if you have more than one DVR, same goes to the Ip adress that shown.

NO.	IP Address	Port	MAC
1	192.168.1.10	34567	00:12:15:51:32:a7
2 3	192.168.1.20 192.168.1.116	34567 34567	00:12:15:51:52:10 00:12:13:07:1e:7a
Device M	IP Search	Add Device	EditDevice
LoginTy	pe ✓ IP Address ess 192 . 168 .	Domain .	ARSP Cloud
Port	34567		
User Na	ime admin	Password	
Zone	one		
Vendor	H264DVR	-	
	C	K Can	cel

14. After adding the IP. Double click at the Device name to add the device

Device Manager	×	Device Manager	×
🖺 🧇 🥕 🏦 🛓 🌉		🔁 🧇 🔊 🛍 🛓 👰	
2 Zone List		(j) Zone List j) one ∭ 1921 165.1.10	
OX		x	

15. The device name will appear such as shown below.



16. To make the camera visible, Click at the black empty box and select the camera one by one. To change the view to (1/4/8/16/) can be choose at the bottom .

