

## M20 & M30 setting

Door Access, Attendance, keypad, fingerprint, doorbell.

Can support up to 30,000 data with 800 user. Each user can be identify up to 10 fingers for finger print.

## PROGRAMING..

Install software from CD.. (Provided)

After done with registration, changed username and password... follow this step.

## DEVICE MANAGER,

To LOAD all USER from the keypad. Or ADD device from the keypad to computer software. Make sure device is connected to Cat6 and got internet connection.

ADD DEVICE by making sure that the IP address and device ID is the same at the software and the DEVICE.



Referring to this Picture..


PLACE = the location of the device.

COMMUNICATION = RS232/ RS485....TCP/IP....USB...P2P...(we currently use TCP/IP)

DEVICE ID : the ID of the device .

PASSWORD = if there is password set at the device. The same password is needed here.

TCP/IP.. this is for the cat6 plugged at the device and the computer need the same network. Make sure the same IP no is key-in to the computer software.



after entering the detail and it is correct. Click on "search" to find the device.

After the device connected.. GET ALL LOG. To get all data that already ADD ed at the device.

## **SYSTEM MANAGER**

Option

Maintenance

Normal ( to set up recods)

Manager (for set up admin )

Program (to overwrite data)

Change Password.

Advance (restore & backup)

## **COMPANY INFO**

**DATA MAINTENANCE**

To set up LOGO

To backup or clear data.

## **ATTENDANCE MANAGER**

Attendance manager.... Store the daily and monthly attendance, leave, + ect.. also can be known as a report.

Attendance rule..... to set up the rule that the worker should follow, like the PJH or the working schedule. Also can be applicable at shift.

Add Attendance.... To ADD the attendance from the new log, different group or different location of a different device.

Leave.... To set certain person leave after filling the leave form so that the report can be accurate.

Schedule.... To set the schedule for each group for their working hours.

Report.....The report of the month can be keep up to 6 month before the data overwrite.

## **USER MANAGEMENT**

To ADD New user.. can be either way from the keypad or from computer software. From computer software can add user and fill up the detail yet for the finger print, still need to register from keypad.

Sync user.... To sync the user those already add from the keypad and the computer. Or else the user will not be updated.

USB user..... You also can sync the user from the keypad by USB Stick. Download the user log from the device and open the USB Stick using the Time Attendance Software.